

Premises & Estate Section, Circle Office Pune,
Canara Bank Building, FP 790 (Part), Near Mangala Theatre,
Shivaji Road, Shivaji Nagar, Pune, Maharashtra. PIN - 411005.
Phone : 020 - 25530622; Email : pecopne@canarabank.com; Website: www.canarabank.com

**BOQ FOR ELECTRICAL WORKS IN BRANCH PREMISES & ATM LOBBY AT:
NER BRANCH, DIST. YAVATMAL (AMRAVATI REGIONAL OFFICE)**

A ELECTRICAL WORKS				
1	MAIN PANEL / DISTRIBUTION BOARDS / MCCBs:			
1.1.	MAIN INCOMER - 100A FP MCCB 16kA in Sheet steel Enclosure Box	Nos.	1.00	
	Supplying & Installing 100A, FP MCCB in IP65W Sheet Steel Enclosure complete, complete with Gland Box, Cable managers, rubber / silicone sealing gasquets, locking arrangement etc. The Box should be placed outside the premises at a suitable location preferably safe from rainfall and accidental human contact.			
1.2.	BUS-BAR: SIT of 100A 415V 4 strip Step Type Bus Bar chamber box complete with enclosure made out of powder coated CRCA having gland plates with conduit knockouts, earthing terminals. The enclosure must have proper insulation and locking arrangement.	Set	1.00	
1.3.	MAIN PANELS / DBs:			
	SITC sheet metal fabricated & powder coated Double Door Type MCB Distribution Boards (surface/flush mounted). DB's shall have MCB/MCCB as incomer, RCCB as sub-incomer & SP/DP/TP MCB as outgoing, complete with Per Phase Isolation. All MCBs of B/C characteristics (B type for Light and Fan load and C type for rest of the load) and 10 KA breaking capacity. The ELCB's, RCCB's, RCBO's should be of 100mA sensitivity. The DB shall have appropriate no. of top & bottom knock outs for outgoing circuits & shall be complete with necessary bus bars, interconnecting terminals & earth studs. All terminations in DB shall be complete with feruling, dressing with lugs & all circuits shall be properly labeled with PVC strip (sticker type) having identification as per the final approval of the Bank / Architect / Consultant.			
1.3.1.	VTPN DB1 - SITC Lighting, AC & Raw Power Main DB (Non-Essential Load)			
	i) 4 way VTPN - MCCB DB,	Nos.	1.00	
	ii) 415V 63Amp. TPN, MCCB (16 KA breaking capacity)	Nos.	1.00	
	iii) 25 A - TP MCB outgoing (LDB)	Nos.	1.00	
	iv) 63 A - TP MCB outgoing (AC & PDB & Spare)	Nos.	1.00	
	v) Blanking plates	Nos.	6.00	
1.3.2.	VTPN DB2 - SITC UPS, ATM & GSB Main DB (Essential Load)			
	i) 4 way VTPN - MCCB DB,	Nos.	1.00	
	ii) 415V 63Amp. TPN, MCCB (16 KA breaking capacity)	Nos.	1.00	
	iii) 25/32 A - SP MCB outgoing (Branch UPS Input, Inverter Input, ATM UPS Input, ATM Lighting & AC DB, Glow Sign Board, Spare Feeders)	Nos.	6.00	
	iv) Blanking plates	Nos.	6.00	
2	DISTRIBUTION BOARDS			
	SITC sheet metal fabricated & powder coated Double Door Type MCB Distribution Boards (surface/flush mounted). DB's shall have MCB/MCCB as incomer, RCCB as sub-incomer & SP/DP/TP MCB as outgoing, complete with Per Phase Isolation. All MCBs of B/C characteristics (B type for Light and Fan load and C type for rest of the load) and 10 KA breaking capacity. The ELCB's, RCCB's, RCBO's should be of 100mA sensitivity. The DB shall have appropriate no. of top & bottom knock outs for outgoing circuits & shall be complete with necessary bus bars, interconnecting terminals & earth studs. All terminations in DB shall be complete with feruling, dressing with lugs & all circuits shall be properly labeled with PVC strip (sticker type) having identification as per the final approval of the Bank / Architect / Consultant.			
2.a	SITC LIGHTING DB1			
	i) 6 way TPN - MCB DB,	Nos.	1.00	
	ii) 25 A - FP MCB, as incomer	Nos.	1.00	
	iii) 25 A - DP 30mA RCCB, as sub-incomer	Nos.	3.00	
	iv) 6/10 A - SP MCB outgoing (6A for Light & Points, 10 A for Sockets)	Nos.	10.00	
	vi) Blanking plates	Nos.	2.00	
2.b	SITC RAW POWER & AC DB			
	i) 6 way TPN - MCB DB,	Nos.	1.00	
	ii) 63 A - TPN MCB	Nos.	1.00	

iii)	40 A - DP 100mA RCCB, as sub-incomer	Nos.	3.00		
iv)	10/16/20/25/32 A - SP MCB outgoing	Nos.	6.00		
vi)	Blanking plates	Nos.	6.00		
2.c	SITC Branch UPS Sub Main DB				
i)	6 way SPN - MCB DB,	Nos.	1.00		
ii)	40 A - DP MCB as incomer	Nos.	1.00		
iii)	40 A - DP 100mA RCCB, as sub-incomer	Nos.	1.00		
iv)	20/32 A - SP MCB outgoing, 1 for UPS Output DB 1 & 1 for UPS Output DB 2	Nos.	2.00		
2.d	SITC Branch UPS Output DB 1 (Essential Load)				
i)	8 way SPN - MCB DB,	Nos.	1.00		
ii)	32 A - DP MCB as incomer	Nos.	1.00		
iii)	6/10/16 A - SP MCB outgoing, 1 Point for CCTV, 1 Point for Data Network rack, 1 Point for Fire Alarm System, 1 Point for Security alarm system, 1 for ATM & 1 No. Spare Feeder	Nos.	6.00		
2.e	SITC Branch UPS Output DB 2 (Non - Essential Load)				
i)	12 way SPN - MCB DB,	Nos.	1.00		
ii)	32 A - DP MCB as incomer	Nos.	1.00		
iii)	6/10/16 A - SP MCB outgoing, for Computer Power Points on Tables, Counters and Work Stations.	Nos.	8.00		
vi)	Blanking plates	Nos.	2.00		
2.f	SITC INVERTER Lighting DB				
i)	12 way SPN - MCB DB,	Nos.	1.00		
ii)	25 A - DP MCB as incomer	Nos.	1.00		
iii)	25 A - DP 30mA RCCB, as sub-incomer	Nos.	1.00		
iv)	6/10A - SP MCB outgoing	Nos.	6.00		
vi)	Blanking plates	Nos.	2.00		
2.g	SITC ATM UPS Output DB				
i)	4 way SPN - MCB DB,	Nos.	1.00		
ii)	25 A - DP MCB as incomer	Nos.	1.00		
iii)	10/16A - SP MCB outgoing	Nos.	2.00		
2.h	SITC ATM L&AC DB				
i)	6 way SPN - MCB DB,	Nos.	1.00		
ii)	32 A - DP MCB as incomer	Nos.	1.00		
iii)	6/20A - SP MCB outgoing	Nos.	3.00		
iv)	Blanking plates	Nos.	2.00		
3	MCB BOXES				
3.a.	SITC 2 way - MCB with Box, <u>for switching OFF Non-Essential Branch UPS output & Inverter Lighting Output (TO BE LOCATED NEAR THE ENTRANCE OF BRANCH NEXT TO VTPN DBs)</u>				
i)	Sheet steel Enclosure Box for DP MCB	Nos.	2.00		
ii)	32/20 A - DP MCB	Nos.	2.00		
3.b.	SITC 2 way - MCB with Box, for Branch UPS Input & Output, ATM UPS Input & Output, for Inverter output				
i)	Sheet steel Enclosure Box for DP MCB	Nos.	5.00		
ii)	32/25/20 A - DP MCB	Nos.	5.00		
3.c.	SITC 4 way - MCB with Box, for Inverter Input				
i)	Sheet steel Enclosure Box for FP MCB	Nos.	1.00		
ii)	25 A - DP MCB	Nos.	1.00		
iii)	25 A - DP 30mA RCCB, as sub-incomer	Nos.	1.00		
3.d.	SITC 6 way - MCB with Box, for Glow Sign Board & Outside Lighting				
i)	Sheet steel Enclosure Box 6Way SP MC Box	Nos.	1.00		
ii)	25 A - DP MCB	Nos.	1.00		
iii)	25 A - DP 30mA RCCB, as sub-incomer	Nos.	1.00		
iv)	10/16A - SP MCB outgoing	Nos.	2.00		
4	AC POINTS - To be drawn from RAW POWER & AC DB (S.No. 2.b) & 2 points for 1.0T ACs from ATM L&AC DB (2.h)				

4.a	Supplying & Installing 20 A Power Socket points complete with MS concealed box, 20A Modular Socket, and 20/25A SPMCB with necessary screws, nylon plug, Saddles, hardware etc. The point cost must be inclusive of 2x4.0 Sq.mm. + 1x2.5 Sq. mm. PVC insulated FRLS Multistrand copper Conductor wires concealed inside 25mm/20 mm PVC conduit. <i>(For High Wall Split AC 1.0T & 1.5T Units)</i>	Nos.	4.00		
	NOTE: Provision should be made in the point wiring for insertion and installation of AC stabilizers with proper terminations using lugs and sealants. The wiring from AC DB to stabilizers and from stabilizers to the actual end point must be concealed in PVC Conduits of appropriate dia.				
4.b	Supplying & laying circuit wiring for 20 A Power Socket points (without any socket / switch <i>(directly controlled by a Individual SP MCBs in AC DB)</i>) with necessary screws, nylon plug, saddles, hardware etc. The point cost must be inclusive of 2x4.0 Sq.mm. + 1x2.5 Sq. mm. PVC insulated FRLS Multistrand copper Conductor wires concealed inside 25mm/20 mm PVC conduit. <i>(For Cassette AC 1.0T / 1.5T Units)</i>	Nos.	2.00		
	The point must include termination of wiring upto the indoor or outdoor unit of the air conditioners, as required, inside MS conduit fixed rigidly on walls complete with clamps, screws etc. (for portion of wiring outside the premises in case point is to be provided up till outdoor unit) without any extra cost.				
	NOTE: Provision should be made in the point wiring for insertion and installation of AC stabilizers with proper terminations using lugs and sealants. The wiring from AC DB to stabilizers and from stabilizers to the actual end point must be concealed in PVC Conduits of appropriate dia.				
5	STRONG ROOM WIRING	Nos.	1.00		
	Supplying & Installing 20 A Power Socket points complete MS concealed box, Modular Switch plate, 20A Modular Socket, controlled by a Modular 20A SP MCB with necessary screws, nylon plug, Saddles, hardware etc. including cost of 2x2.5.0 sqmm + 1x1.5 sqmm PVC insulated FRLS copper Wires and 25mm/20 mm PVC conduit, <i>For Strong Room / Cash room Entrance as It's Lighting circuit control from outside. Lighting switch board inside the Strong room / Cash room to be connected using, 2 Mtr. 3 core 1.5 sq mm flexible copper cable with a 15 A plug top from this power socket installed outside the room (rate should be given inclusive of flexible cable, plug top, circuit and flexible conduit for the 2 Mtr. Link)</i>				
6	CABLES & TERMINATIONS				
	Supply and Laying of following LT cables conforming to IS 1554 (part 1) with necessary M.S. clamps. All such cables shall be provided with temporary labeling at every 20 mtr. & then finally with metal identification tags showing the size & the location from/to the specific panel/DB; at both the ends. The rate is inclusive of termination charges				
6.1	Aluminium Armoured Cables				
	4 C x 50 Sq.mm Aluminium AYFY Armoured Cables, 1. From Energy Meter to MAIN INCOMER (S.No. 1.1.) 2. From MAIN INCOMER (S.No. 1.1.) to 100A Bus Bar (S.No. 1.2.) 3. From Bus-Bar (S.No. 1.2.) to VTPN DB1 (S.No. 1.3.1.) 4. From Bus-Bar (S.No. 1.2.) to VTPN DB2 (S.No. 1.3.2.)	Rmt	10.00		
6.2	Copper Flexible Cables				
6.2.a.	2C x 4 Sq.mm. Copper Conductor Flexible Cable + 2.5 Sq. mm. PVC Insulated Multistrand Copper Conductor wire for earth, 1. From VTPN DB2 (S.No. 1.3.2.) to ATM UPS Input MC Box (S.No. 3.b.) 2. From ATM UPS Input MCB Box (S.No. 3.b.) to ATM UPS 3. From ATM UPS to ATM UPS Output MCB Box (S.No. 3.b.) 4. From ATM UPS Output MCB Box (S.No. 3.b.) to ATM UPS Output DB (S.No. 2.g) 5. From VTPN DB2 (S.No. 1.3.2.) to ATM L&AC DB (S.No. 2.h.) 6. From VTPN DB2 (S.No. 1.3.2.) to Inverter Input MCB Box (S.No. 3.c.) 7. From Inverter Input MCB Box (S.No. 3.c.) to inverter 8. From Inverter to inverter output MC Box (S.No. 3.b.) 9. From VTPN DB2 (S.No. 1.3.2.) to GSB MCB Box (S.No. 3.d) 10. From GSB MCB Box (S.No. 3.d) to Glow Sign Board 11. From Branch UPS Sub Main DB SP MCB1 & Neutral (S.No. 2.c.iv) to Input side of DP MB Incomer of Branch UPS Output DBs 1 (S.No. 2.d.ii)	Rmt	90.00		
6.2.b.	2C x 6 Sq.mm. Copper Conductor Flexible Cable + 4.0 Sq. mm. PVC Insulated Multistrand Copper Conductor wire for earth, 1. From VTPN DB2 (S.No. 1.3.2.) to Branch UPS Input MCB Box (S.No. 3.b.) 2. From Branch UPS MCB Box (S.No. 3.b.) to Branch UPS 3. From Branch UPS to Branch UPS Output MCB Box (S.No. 3.b.) 4. From Branch UPS Output MCB Box SPMCB1 (S.No. 3.b.) to Branch UPS Sub Main DB (S.No. 2.c.) 5. From Branch UPS Sub Main DB SPMCB2 & neutral (S.No. 2.c.iv) to MCB Box (S.No. 3.a) at entrance 6. From MCB Box at entrance (S.No.3.a) to Input side of DP MB Incomer of Branch UPS Output DB 2 (S.No. 2.e.ii)	Rmt	85.00		

6.2.c.	4C x 4 Sq.mm. Copper Conductor Flexible Cable + 2.5 Sq. mm. PVC Insulated Multistrand Copper Conductor wire for earth, <i>1. From VTPN DB1 to Lighting DB 1 (S.No. 2.a)</i>	Rmt	20.00		
6.2.d.	4C x 10 Sq.mm. Copper Conductor Flexible Cable + 6.0 Sq. mm. PVC Insulated Multistrand Copper Conductor wire for earth, <i>1. From VTPN DB to Raw Power & AC DB (S.No. 2.b)</i>	Rmt	15.00		
6.2.e.	3C x 2.5 Sq.mm. Copper Conductor flexible cable, <i>1. From inverter output MCB Box (S.No. 3.b.) to MCB Box (S.No. 3.a) at entrance</i> <i>2. From MCB Box (S.No. 3.a) at entrance to Input side of DP MCB Incomer of inverter lighting DB (S.No. 2.f.ii)</i>	Rmt	50.00		
7 POINT WIRINGS					
	Complete job shall include cutting chiseling in walls, floor and making good of all chases / cuts etc. with combination of cement-mortar, including painiting with type and shade of existing wall. The work shall be completed to the satisfaction of Bank. NO CABLE / WIRE / CONDUIT SHALL BE VISIBLE IN THE BRANCH HALL / CUSTOMER LOBBY / STAFF WORKING AREA. (No seperate measurements for circuit wiring & PVC Conduits)				
	Complete job shall include cutting chiseling in walls, floor and making good of all chases / cuts etc. with combination of cement-mortar, including painiting with type and shade of existing wall. The work shall be completed to the satisfaction of Bank. NO CABLE / WIRE / CONDUIT SHALL BE VISIBLE IN THE BRANCH HALL / CUSTOMER LOBBY / STAFF WORKING AREA.				
7.1.	UPS Points				
	THE POINTS FOR ESSENTIAL LOADS AND NON-ESSENTIAL LOADS SHOULD BE POWERED THROUGH SEPARATE D.B.s AS MENTIONED BELOW. NO MIXING SHOULD BE DONE				
7.1.a.	Non-Essential UPS Power points (From 12 Way SPN DB)	No	7.00		
Note	For Computer Points in Counters and Tables and for points for Printers etc., to be powered through Branch UPS Output DB 2 (S.No. 2.e)				
	Supplying & Installing Primary UPS or Stabilized Power points on workstations / tables for computers using using 2x2.5 Sq.mm. + 1x1.5 Sq. mm. PVC insulated multistanded FRLS Grade flexible copper wires through 25mm size MMS Grade PVC conduites, laid on surface above false ceiling and taken upto table top using 25/20 mm size MMS Grade PVC rigid or flexible conduits run within wooden or metal partitions.				
	Each point consisting of 2 Nos of 6A, 5 Pin Modular sockets and 1 No. of 16A, 6 pin socket controlled by 1 No 20A Modular switch & Indicator lamp, wired together forming one point. Earth wire to be of Green colour only. Switch should be above table top & sockets with indicator should be below table top.				
7.1.b.	Essential UPS Power points (From 8 Way SPN DB)	No	4.00		
Note	For CCTV System, Fire Alarm System, Burglar Alarm System, Networking Rack, to be powered through Branch UPS Output DB 1 (S.No. 2.d)				
Note	For ATM UPS Output, to be powered through ATM UPS Output DB (S.No. 2.g)				
	Supplying & Installing Primary UPS or Stabilized Power points on workstations / tables for computers using using 2x2.5 Sq.mm. + 1x1.5 Sq. mm. PVC insulated multistanded FRLS Grade flexible copper wires through 25mm size MMS Grade PVC conduites, laid on surface above false ceiling and taken upto table top using 25/20 mm size MMS Grade PVC rigid or flexible conduits run within wooden or metal partitions.				
	Each point consisting of 2 Nos of 6A, 5 Pin Modular sockets and 1 No. of 16A, 6 pin socket controlled by 1 No 20A Modular switch & Indicator lamp, wired together forming one point. Earth wire to be of Green colour only. Switch should be above table top & sockets with indicator should be below table top.				
7.2.	RAW POWER POINTS				
	POINTS' QUANTITY TO BE KEPT STRICTLY AS MENTIONED BELOW				
7.2.a.	Primary Raw power points (To be drawn from RAW POWER & AC DB (S.No. 2.b)) <i>for Printers / Cash counting machine / Water cooler etc.</i>	No	2.00		
	Supplying & Installing Primary 20 A Power Socket points using 2x4.0 Sq.mm. + 1x2.5 Sq.mm. PVC insulated multistanded FRLS Grade flexible copper wires (with proper color code) pulled through heavy gauge PVC conduits directly from Power & AC DB.				
	Each point consisting of 1 Nos of 20 A Modular sockets controlled by 1 Nos of 20A Modular switch, wired together forming a point. Earth wire to be of Green colour only.				
7.2.b.	Secondary Raw power points (To be looped from Primary Raw Power Points (S.No.8.2.a.) - for Counters & Tables & misc.	No	2.00		
	Supplying & Installing Primary 10/20 A Power Socket points using 2x2.5 Sq.mm. + 1x1.5 Sq.mm. PVC insulated multistanded FRLS Grade flexible copper wires (with proper color code) pulled through heavy gauge PVC conduits looped from Prima				

	Each point consisting of 1 Nos of 10/20 A Modular sockets controlled by 1 Nos of 20A Modular switch, wired together forming a point. Earth wire to be of Green colour only.				
	Only 1 Secondary Raw power point must be looped from the Primary Power Point. A combination of only 1 primary point & 1 secondary point to be served by one circuit taken from Raw Power & AC DB				
7.3.	LIGHT POINT WIRING				
	SITC of following concealed point wiring using 1100V grade 3x1.5 Sq. mm. Multistrand copper conductor PVC insulated FRLS wires (with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to light points shall be drawn in flexible PVC conduit with adaptor & cover for junction box & crimp type lugs at both ends. Each circuit feeding not more than average 12 points (800 watts). The rate shall include circuit wiring (2x2.5 Sq. mm. + 1x1.5 sq.mm.) from Lighting DB to switchboard and to the fixtures. <i>(No seperate measurements for circuit wiring & PVC Conduits)The First Point will be considered as Primary Point and balance points as Secondary Points.</i>				
7.3.a.	Primary Light points, Powered from LIGHTING DB (S.No. 2.a)	No	26.00		
	SITC 5/6A Primary light points including MS concealed box, grid plate, 6A switch & circuit wiring through LDBs				
7.3.b.	Primary Light points, Powered from INVERTER Lighting DB (S.No. 2.f)	No	10.00		
	SITC 5/6A Primary light points including MS concealed box, grid plate, 6A switch & circuit wiring through Inverter DB				
7.3.c.	Secondary Light points, to be looped from Primary Light Points (S. No. 7.3.a.)	No	12.00		
	SITC 5/6A Secondary light points looped from primary light point.				
7.3.d.	Independent 5/6A socket points, Powered from LIGHTING DB (S.No. 2.a)	No	3.00		
	SITC of Primary 5/6A Socket points using circuit wiring (with proper color code) pulled through medium gauge PVC conduits.				
	Each point consisting of 1 Nos 5 pin of 5/6A sockets controlled by 1 Nos of 6A switch, wired together forming a point with Green colour Earth wire.				
7.3.e.	Dependent 5/6 A socket points (on Board plug points), Powered from LIGHTING DB (S.No. 2.a)	No	6.00		
	SITC Secondary 5/6A Socket points using circuit wiring (with proper color code) pulled through haevy gauge PVC conduits. These points are installed on the Lighting Switch Board.				
	Each point consisting of 1 Nos of 5 pin 5/6A sockets controlled by 1 Nos of 6A switch, wired together forming a point. Earth wire to be of Green colour only.				
7.3.f.	Exhaust fan points, Powered from LIGHTING DB (S.No. 2.a)	No	3.00		
	SITC of concealed point wiring for Exhaust fan using 1100V grade 3x1.5 Sq. mm. Multistrand Copper Conductor PVC insulated FRLS wires (with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to fan points shall be drawn in flexible PVC conduit with adaptor & cover for junction box & crimp type lugs at both ends.				
	The rate shall include circuit wiring (2x2.5 Sq. mm. + 1x1.0 Sq. mm.) from Lighting DB to switchboard and to the Exhaust fan and Wall fan. (No seperate measurements for circuit wiring & PVC Conduits)				
	Each Exhaust Fan will be operated on seperate switch, Rate should be including the cost of 6 A switch, 4 way closed 5A connector & Mounting Plates & Ceiling Rose.				
7.3.g.	Wall Fan points, Powered from INVERTER Lighting DB (S.No. 2.f)	No	12.00		
	SITC of concealed point wiring for Exhaust fan using 1100V grade 3x1.5 Sq. mm. Multistrand Copper Conductor PVC insulated FRLS wires (with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to fan points shall be drawn in flexible PVC conduit with adaptor & cover for junction box & crimp type lugs at both ends.				
	The rate shall include circuit wiring (2x2.5 Sq. mm. + 1x1.0 Sq. mm.) from Lighting DB to switchboard and to the Exhaust fan and Wall fan. (No seperate measurements for circuit wiring & PVC Conduits)				
	Each wall fan will be operated on seperate switch, Rate should be including the cost of 5/6 A switch, 3 pin 5/6A socket, gang box & Mounting Plates				
7.3.h.	Ceiling fan points, Powered from LIGHTING DB (S.No. 2.a)	No	3.00		
	SITC Ceiling Fan point operated on seperate switch shall be Controlled by 2 Module, 5-Step Fan regulator, Rate should be including the cost of Fan hook, Suspending suitable fan rod, Connecting cord and Step type Fan Regulator				
8.1.	Indicator Lights point (for Non-Essential VTPN DB1)	Set	1.00		
	Providing and fixing R-Y-B Indicator LED Light Assembly concealed in display boxing along with Point Wiring to be done with 4C 1.5 Sq.mm. PVC insulated multistanded FRLS Grade flexible copper Cable drawn through Heavy gauge PVC conduit from Respective DB / MCCB. The route of the indicator wiring to be as under:				

	4C 1.5 Sq.mm. cable looped from Output side of MCCB of Main Panel VTPN DB1 (1.3.1. - (ii)) TO R-Y-B Indicator Lamp Near Entrance				
	R-Y-B Colour Indicator Lamps for Non-Essential Power VTPN DB				
	The indicators must be placed next to the main entrance at a suitable location so that they are visible through any one of the branch's CCTV Cameras				
	The looping of the cable must be done carefully using proper lugs and must be fastened rigidly to avoid faults				
8.2.	Indicator Lights point (for Non-Essential UPS Output Load & Inverter Lighting Load)	Set	2.00		
	Providing and fixing Single Indicator LED Light of mentioned colour concealed in display boxing along with Point Wiring to be done with 2C 1.5 Sq.mm. PVC insulated multistandard FRLS Grade flexible copper Cable drawn through Heavy gauge PVC conduit from Respective DB / MCCB. The route of the indicator wiring to be as under:				
	1. 2C 1.5 Sq.mm. cable looped from Output side of DPMCB1 of MB Box near branch entrance (3.a. - (ii)) to R-Led Indicator				
	2. 2C 1.5 Sq.mm. cable looped from Output side of DPMCB2 of MB Box near branch entrance (3.a. - (ii)) to B-Led Indicator				
	R-Indicator LED Light Assembly concealed in display boxing for Non Essential Branch UPS Output				
	B-Indicator LED Light Assembly concealed in display boxing for Inverter Lighting Output				
	Red Colour Indicator lamp for Non-Essential UPS Output				
	Blue Colour Indicator lamp for Inverter Lighting Output				
	The indicators must be placed next to the main entrance at a suitable location so that they are visible through any one of the branch's CCTV Cameras				
	The looping of the cable must be done carefully using proper lugs and must be fastened rigidly to avoid faults				
	9 EARTHING SYSTEM				
9.1.	Plate Earthing				
	S & I of Earthing Pit / Earth Electrode Station into the true ground level by using GI / Copper Plate type earthing with necessary excavation in soft soil, including Pouring Charcoal & Salt (Approximately) 50kg each per Pit with Predrilled 50mm dia B class GI Pipe-2.5 Mtr In length, GI Funnel with wiremesh, 35 x 5mm GI/Cu Earthing Strip, Complete job with necessary construction of appropriate sized Earthing PIT masonry Chamber with providing CI hinged chamber cover, Nutbolts, Earthing Testing Link, Hardware, Numbering of Chamber by using water proof paint. For more details refer IS 3043-1987 Brazing for Cu & Welding for GI Plate to pipe & Strip shall be done with coating by anti-corrosive paint				
9.1.a.	CU Plate earthing.	No	3.00		
	Copper earthing pit made up of 600 x 600 x 3 mm thick, copper electrode including 25 x 5 mm Copper strip.				
9.2.	Earthing Wires				
	SITC of insulated copper earthing wire laid through 20 mm PVC conduits from separately made earth pit to the equipment in following sizes				
9.2.a.	Single core, 4 sqmm FRLS PVC insulated multi threaded, flexible copper wire laid through 20 mm size, MMS Grade PVC Conduites for Raw Power Earthing.	Rmt	50.00		
9.2.b.	Single core, 6 sqmm FRLS PVC insulated multi threaded, flexible copper wire laid through 20 mm size, MMS Grade PVC Conduites for UPS power Earthing.	Rmt	50.00		
9.3.	Main Earth Bus	No	2.00		
	Supplying & Installing of Main bus for isolated earth comprising of 200mm x 40mm x 6mm thick copper bar fixed on insulated support and having 20 nos of holes and nut bolts studs for clamping the earth leads,all contained in MS/PVCbox of size 300mm x 200mm x 50mm deep and having transparent acrylic inspection cover as approved by Bank / Architect.				
10	TELEPHONE / VOICE CABLING AND OUTLETS	No	2.00		
	Providing and laying 2 Pair Grey Color 0.5mm Tinned Cu , PVC insulated cable for Telephone / Voice, laid through 20 / 25 mm size, MMS Grade PVC Conduites and Supplying & terminating with RJ-11 Telephone Jack / Outlet with face plates in suitable modular PVC / MS box from EPABX / Krone Tag Box to the work stations and terminate the other on a 10 pair Krone module installed in a Krone Tag box, complete 10-pair 0.5 Sq. mm. size Telephone Cable for incoming with numbering of each cable with Ferule and Telephone Connection Chart (No seperate measurements for PVC Conduits)				
11	DATA CABLING SYSTEM				
11.1.	Data points	No	9.00		

