

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
<b>All wires should be of FRLS make</b>					
Type of wiring	Concealed				
Casing capping (as per approval)	Modi make/ Precision (ISI grade)				
PVC pipe and accessories	Precision / Polycab / Swastik (ISI make)				
Wires	Polycab / Finolex / R R kabel make with				
Computer Data Cable	D-Link / Molex / Awaya make				
cable/ wires	Polycab / Finolex / R R kabel make (ISI				
MCB / MCB DB	L & T, Legrand / Siemens (ISI)				
ELMCB	L & T, Legrand / Siemens (ISI)				
Ft. tubes & fixtures	Philips / Wipro / Crompton / Havells /				
Ceiling fans	Crompton Greaves / Havells / Usha				
screws	Nettlefold				
Earthing material	Strictly Bare Copper and with charcoal				
Switch fuse unit	L & T make (ISI)				
Switches/sockets & accessories	Legrand / Anchor Roma Modular type				
switchboards	Concealed modular type				
Copper strip type busbar	Havells / Standard make				
ONLINE UPS	Fuji / Vertiv				
SMF Batteries	Exide / Amaron				
Offline UPS / Inverter	Microtek / Havells				
Tubular Batteries	Exide / Amaron				
<b>SR</b>	<b>SUMMARY</b>				<b>AMOUNT</b>
<b>A</b>	<b>TOTAL OF MAIN PANEL / DB's / MCCBs :-</b>				-
<b>B</b>	<b>TOTAL OF CABLES &amp; TERMINATIONS</b>				-
<b>C</b>	<b>TOTAL OF POINT WIRING</b>				-
<b>D</b>	<b>TOTAL OF FIXTURES</b>				-
<b>E</b>	<b>TOTAL OF EARTHING SYSTEM</b>				-
<b>F</b>	<b>TOTAL OF TELEPHONE SYSTEM</b>				-
<b>G</b>	<b>TOTAL OF DATA CABLING SYSTEM</b>				-
<b>H</b>	<b>TOTAL FOR MISCELLANEOUS WORKS</b>				-
	<b>TOTAL FOR ELECTRICAL WORKS</b>				-
	Amt. in Rs.				Only
					GST extra
<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>SR. NO.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
<b>A</b>	<b>MAIN PANEL / DISTRIBUTION BOARDS / MCCBs :-</b>				
<b>1</b>	<b>Meter room Mains MCCB's</b>				
	<b>Supplying &amp; Installing 80A / 100A, FP MCCB in Sheet Steel Enclosure, complete with Gland Box etc</b>				
	a. 80A / 100 A FP MCCB 16kA	Nos.	1.00		-
	<b>Make : Legrand, Type : DPX3 160 with Thermal &amp; Magnetic protection Unit</b>				
	b. Sheet steel Enclosure Box for FP MCCB	Nos.	1.00		-

<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>Sr. No.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
<b>2</b>	<b>MCB DISTRIBUTION BOARDS</b>				
	SITC sheet metal fabricated & powder coated Double Door Type MCB Distribution Boards (surface/flush mounted). DB's shall have MCB/MCCB as incomer, RCCB as sub-incomer & SP/DP/TP MCB as outgoing, complete with Per Phase Isolation. All MCBs of C characteristics and 10 KA breaking capacity & ELCB's, RCCB's, RCBO's should be of 100mA sensitivity. The DB shall have appropriate no. of top & bottom knock outs for outgoing circuits & shall be complete with necessary bus bars, interconnecting terminals & earth studs. All terminations in DB shall be complete with feruling, dressing with lugs & all circuits shall be properly labeled with PVC strip (sticker type) having identification as per the final approval of the Consultant.				
<b>2.1</b>	<b>SITC Mains DB,</b>				
	<b>6 way VTPN - MCCB DB,</b>	Nos.	1.00		-
	<b>80/100 A - TP MCCB, 16kA</b>	Nos.	1.00		-
	<b>25 A - TP MCB outgoing (LDB)</b>	Nos.	2.00		-
	<b>63 A - TP MCB outgoing (AC DB &amp; Spare)</b>	Nos.	2.00		-
	<b>25/32 A - SP MCB outgoing (UPS Input / Inverter DB, Signage / ATM DB)</b>	Nos.	6.00		-
	<b>Blanking plates</b>	Nos.	0.00		-
<b>2.2</b>	<b>SITC LIGHTING DB</b>				
	<b>6 way TPN - MCB DB,</b>	Nos.	1.00		-
	<b>25 A - FP MCB, as incomer</b>	Nos.	1.00		-
	<b>25 A - DP 30mA RCCB / ELCB, as sub-incomer</b>	Nos.	3.00		-
	<b>6/10 A - SP MCB outgoing</b>	Nos.	12.00		-
<b>2.3</b>	<b>SITC RAW POWER &amp; AC DB</b>				
	<b>6 way TPN - MCB DB,</b>	Nos.	1.00		-
	<b>63 A - TPN MCB</b>	Nos.	1.00		-
	<b>40 A - DP 100mA RCCB / ELCB, as sub-incomer</b>	Nos.	3.00		-
	<b>16/20/25/32 A - SP MCB outgoing</b>	Nos.	12.00		-
<b>2.4</b>	<b>SITC UPS Output DB</b>				
	<b>6 way SPN - MCB DB,</b>	Nos.	1.00		-
	<b>32 A - DP MCB as incomer</b>	Nos.	1.00		-
	<b>32A - SP MCB outgoing, .... for Branch UPS DB</b>	Nos.	2.00		-
	<b>16A - SP MCB outgoing, .... for CCTV, Network rack, Security alarm system etc</b>	Nos.	2.00		-
<b>2.5</b>	<b>SITC BRANCH UPS DB</b>				
	<b>16 way SPN - MCB DB,</b>	Nos.	1.00		-
	<b>32 A - DP MCB as incomer</b>	Nos.	2.00		-
	<b>16/20A - SP MCB outgoing</b>	Nos.	12.00		-

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
Sr. No.	ITEM	UNIT	QTY	RATE	AMOUNT
2.6	<b>SITC INVERTER Lighting DB</b>				
	<b>8 way SPN - MCB DB,</b>	Nos.	1.00		-
	<b>25 A - DP MCB as incomer</b>	Nos.	1.00		-
	<b>6/10A - SP MCB outgoing</b>	Nos.	4.00		-
2.7	<b>SITC ATM LDB / AC DB</b>				
	<b>6 way SPN - MCB DB,</b>	Nos.	1.00		-
	<b>32 A - DP MCB as incomer</b>	Nos.	1.00		-
	<b>10/16/20A - SP MCB outgoing</b>	Nos.	4.00		-
2.8	<b>SITC ATM UPS Output DB</b>				
	<b>6 way SPN - MCB DB,</b>	Nos.	1.00		-
	<b>16/20 A - DP MCB as incomer</b>	Nos.	1.00		-
	<b>10/16A - SP MCB outgoing</b>	Nos.	4.00		-
2.9	<b>MCB BOX</b>				
a.	<i>SITC 4 way - MCB with Box, for switching off the lighting DB near main gate to switch OFF all the light points after office hours</i>				
	<b>Sheet steel Enclosure Box for FP MCB</b>	Nos.	1.00		-
	<b>32/25 A - FP MCB</b>	Nos.	1.00		-
b.	<i>SITC 4 way - MCB with Box, for switching off the AC DB near main gate to switch OFF all the AC's after office hours</i>				
	<b>Sheet steel Enclosure Box for FP MCB</b>	Nos.	1.00		-
	<b>63 A - TPN MCB</b>	Nos.	1.00		-
c.	<i>SITC 2 way - MCB with Box, for Cassette AC, at Out Door Unit</i>				
	<b>Sheet steel Enclosure Box for DP MCB</b>	Nos.	4.00		-
	<b>32 A - DP MCB</b>	Nos.	4.00		-
d.	<i>SITC 2 way - MCB with Box, for UPS Input / Output and for switching OFF UPS outputs to branch</i>				
	<b>Sheet steel Enclosure Box for DP MCB</b>	Nos.	3.00		-
	<b>32/25 A - DP MCB</b>	Nos.	3.00		-
e.	<i>SITC 2 way - MCB with Box, for Signage and for switching OFF Inverter outputs to branch</i>				
	<b>Sheet steel Enclosure Box for DP MCB</b>	Nos.	2.00		-
	<b>20/25 A - DP MCB</b>	Nos.	2.00		-

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
Sr. No.	ITEM	UNIT	QTY	RATE	AMOUNT
3.0	<b>Signage Timer</b>				
	Supplying and Installing programmable <b>Digital Timer</b> microcontroller based with real time clock to operate on derived switching "ON" and switching "OFF" glow sign board light as per daily sunset and sunrise respectively automatically having 4 digit LED continuous time display erected in M.S. box.	No.	0.00		-
4.0	<b>Supplying &amp; Installing 10/20 A Modular Power Socket points complete with MS concealed box, Modular Switch plate, 20A Modular Socket, controlled by a Modular 20 / 25A SP MCB</b> with necessary screws, nylon plug, Saddles, hardware etc. <b>including cost of 3 x 4.0 sqmm</b> PVC insulated FRLS copper Wires and 25mm/20 mm PVC conduit, <i>For ATM UPS &amp; Inverter Input &amp; Output connections</i>	Nos.	4.00		-
	Rate in words :-				
c	<b>Supplying &amp; Installing 20 A Power Socket points complete with MS concealed box, 20A Modular Socket, without local switch (directly controlled by a 20 / 25A SP MCB in AC DB)</b> with necessary screws, nylon plug, Saddles, hardware etc. <i>For High Wall Split AC Units</i>	Nos.	4.00		-
	including cost of 2x4.0 sqmm + 1x2.5 sqmm PVC insulated FRLS copper Wires and 25mm/20 mm PVC conduit, <i>For High Wall Split AC Units</i>				
	Rate in words :-				
d.	<b>Supplying &amp; laying circuit wiring for 20 A Power Socket points (without any socket / switch (directly controlled by a 20 / 25A SP MCB in AC DB)</b> with necessary screws, nylon plug, saddles, hardware etc. by laying 2x4.0 sqmm + 1x2.5 sqmm PVC insulated FRLS copper Wires through 25mm/20 mm PVC conduits, <i>For Cassette AC Units</i>	Nos.	2.00		-
	including cost of 2x4.0 sqmm + 1x2.5 sqmm PVC insulated FRLS copper Wires and 25mm/20 mm PVC conduit, <i>For Cassette AC Units</i>				
	Rate in words :-				

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
Sr. No.	ITEM	UNIT	QTY	RATE	AMOUNT
	<b>For Strong Room</b>				
e	Supplying & Installing 20 A Power Socket points complete MS concealed box, Modular Switch plate, 20A Modular Socket, controlled by a Modular 20A SP MCB with necessary screws, nylon plug, Saddles, hardware etc. including cost of 2x2.5.0 sqmm + 1x1.5 sqmm PVC insulated FRLS copper Wires and 25mm/20 mm PVC conduit, For Strong Room / Cash room Entrance as It's Lighting circuit control from outside. Lighting switch board inside the Strong room / Cash room to be connected using, 2 mets of 3 core 1.5 sq mm flexible copper wires/ cable with 15 A plug top from this power socket installed outside the room ( rate should be given inclusive of flexible cable, plug top and circuit )	Nos.	1.00		-
	<b>Indicator Light points</b>	No	4.00		0.00
	R-Y-B Indicator Light point from Main Power DB to Banking area, for indication of Mains power supply with wiring, indicator lamps etc., easily visible from the Exit / Entrance Door, so that the Last Person to leave the Branch / office should Turn OFF the Power Supply (MCB) Located in Power DB's to switch Off the Lighting, fans, AC's etc.				
	Each Indicator Light Point Wiring to be done with 3 X 1.5 Sq.mm. PVC insulated multistanded FRLS Grade flexible copper wires / 3 core 1.5 sq.mm flexible cable drawn through Heavy gauge PVC conduit from Respective DB Power to the Respective Colored Indicator Lamp.				
	Raw Power to be written / Identified on the respective DB with Red Colour				
	UPS Power to be written / Identified on the respective				
	Lighting Power to be written / Identified on the				
	Inverter Power to be written / Identified on the respective DB with Green Colour				
	<b>A. TOTAL OF MAIN PANEL / DB's / MCCBs :-</b>				<b>0.00</b>

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
SR. NO.	ITEM	UNIT	QTY	RATE	AMOUNT
<b>B</b>	<b>CABLES &amp; TERMINATIONS</b>				
	Supply and Laying of following LT cables conforming to IS 1554 (part 1) with necessary M.S. clamps. All such cables shall be provided with temporary labeling at every 20 mtr. & then finally with metal identification tags showing the size & the location from/to the specific panel/DB at both the ends. The cost shall include terminations of all the armoured cables using Siemens type single compression, chrome plated brass cable glands & crimp type tin copper lugs, Bimetallic lugs are to be provided wherever two different type conductors are present, Insulation tape etc. as required complete with earthing of glands.				
<b>1</b>	<b>Aluminium Armoured Cables</b>				
a.	3.5C x 50 Sq.mm Aluminium AYFY Armoured Cables, <i>from MSEB Meter to Main DB</i>	Rmt	30.00		-
	Rate in words :-				
<b>2</b>	<b>Copper Flexible Cables</b>				
a.	4C x 2.5 Sq.mm Copper Flexible Cables, <i>from UPS Output to UPS DB Incoming MCB</i>	Rmt	36.00		-
	Rate in words :-				
b.	4C x 6 Sq.mm Copper Flexible Cables, <i>from Mains DB to Raw Power &amp; AC DB Incoming MCB</i>	Rmt	40.00		-
	Rate in words :-				
c.	4C x 4 Sq.mm Copper Flexible Cables, <i>from Main DB to UPS Input MCB &amp; Main DB to Lighting DB Incoming MCB</i>	Rmt	26.00		-
	Rate in words :-				
<b>3</b>	<b>Flexible cables</b>				
	Supplying & laying following size of 1.1 KV grade PVC insulated flexible copper cables through the <b>Metalic Flexible Pipe</b> neatly clamped where ever required using Spacer plates, GI saddles, including fixing with PVC / Brass glands and termination of cables using suitable crimp type tin copper lugs at both ends.				
a	4 C x 10 sq.mm. Cu flexible cables, <i>for UPS Input MCB to UPS terminal</i>	Rmt	0.00		-
	Rate in words :-				
b	2 C x 6 sq.mm. Cu flexible cables, <i>for UPS Output MCB to UPS terminal</i>	Rmt	0.00		-
	Rate in words :-				
c	3 C x 2.5 sq.mm. Cu flexible cables, <i>for Signage</i>	Rmt	90.00		-
	Rate in words :-				
	<b>B. TOTAL OF CABLES &amp; TERMINATIONS</b>				-

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
SR. NO.	ITEM	UNIT	QTY	RATE	AMOUNT
<b>C</b>	<b>POINT WIRING</b>				
<b>1</b>	<b>POWER POINTS</b>				
	SITC of following concealed Power Point Wiring using 1100V grade 3C x 2.5 sq.mm. PVC insulated, PVC Sheathed White Colored flexible copper FRLS cable, laid through 20mm / 25mm size MMS Grade, PVC conduits. All cabling / conduiting below false ceiling shall be concealed. Each circuit feeding not more than 3 Tables / Work Stations). The rate shall include cabling including conduit cost from DB to mentioned Power Points. <b>(No separate measurements for circuit wiring &amp; PVC Conduits)</b>				
<b>a.</b>	<b>Primary UPS points</b>	No	10.00		-
	Rate in words :-				
	Supplying & Installing <b>Primary UPS or Stabilized Power points</b> on workstations / tables for computers using <b>3C x 2.5 Sq.mm PVC sheathed white color flexible copper FRLS wires/ cable pulled through 25mm size MMS Grade PVC conduites</b> , laid on surface above false ceiling and taken upto table top using 25/20 mm size MMS Grade PVC rigid or flexible conduits run within wooden or metal partitions.				
	Each point consisting of <b>2 Nos of 6A, 5 Pin Modular sockets and 1 No. of 6/16A, 6 pin socket controlled by 1 No 20A Modular switch</b> , wired together forming one point. Earth wire to be of Green colour only. <b>Switch should be above table top &amp; sockets should be below table top</b>				
	<b>Only 3 tables served by one circuit from UPS DB.</b> The Rate should be including the cost of Conduits, wires/ Cables, Switch boards, internal looping wires, necessary Gang Box, PVC box, Modular Plates of other color, Modular Switches, Sockets, Compete Job with necessary screws, nylon plug, Saddles, hardware. Etc. All Switch Boards should be Properly numbered for identifications.				
<b>b.</b>	<b>Secondary UPS points</b>	No	2.00		-
	Rate in words :-				
	Supplying & Installing <b>Secondary UPS or Stabilized Power points</b> on workstations / table for computers using 3C x 2.5 Sq.mm PVC sheathed white color flexible FRLS copper wires/ cable pulled through 25mm size MMS Grade PVC conduites, laid on surface above false ceiling and taken upto table top using 25/20 mm size MMS Grade PVC rigid or flexible conduits run within wooden or metal partitions.				

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
Sr. No.	ITEM	UNIT	QTY	RATE	AMOUNT
	Each point consisting of <b>2 Nos of 10A, 5 Pin Modular sockets and 1 No. of 6/16A, 6 pin socket controlled by 1 No 20A Modular switch</b> , wired together forming one point. Earth wire to be of Green colour only. <b>Switch should be above table top &amp; sockets should be below table top</b>				
	<b>for 2 table served by the same circuit from adjacent Primary point.</b> The Rate should be including cost of wires/ Cable, Switch board internal looping wires, necessary Gang Box, PVC box, Modular Plate of other color , Modular Switches, Sockets, Complete Job with necessary screws, nylon plug, Saddles, hardware. Etc. All Switch Boards should be Properly numbered for identifications.				
<b>c.</b>	<b>Primary 10/20 A power points, for Printers / Pantry / Hot Plate / Water cooler etc</b>	No	2.00		-
	Rate in words :-				
	Supplying & Installing <b>Primary 10/20 A Power Socket points</b> using 2 X 4.0 Sq.mm. + 1 X 1.0 Sq.mm. PVC insulated multistanded FRLS Grade flexible copper wires (with proper color code) pulled through haevy gauge PVC conduits.				
	Each point consisting of <b>1 Nos of 10/20 A Modular sockets controlled by 1 Nos of 20A Modular switch</b> , wired together forming a point. Earth wire to be of Green colour only.				
	Only 2 Sockets served by one circuit taken from Raw Power & ACDB				
<b>d.</b>	<b>Secondary 5/15 A power points, for Printers / Pantry / Hot Plate / Water cooler</b>	No	0.00		-
	Rate in words :-				
	Supplying & Installing <b>Secondary 10/20 A Power Socket points</b> using 2 X 2.5 Sq.mm + 1 X 1.0 Sq.mm PVC insulated multistanded FRLS Grade flexible copper wires (with proper color code ) pulled through haevy gauge PVC conduits.				
	Each point consisting of <b>1 Nos of 6/16 A Modular sockets controlled by 1 Nos of 20A Modular switch</b> , wired together forming a point. <b>Switch should be above table top &amp; sockets should be below table top</b>				
	The circuit should be taken from another Primary 15 A Power Socket Point only, whose circuit taken from Raw Power & ACDB				



SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
SR. NO.	ITEM	UNIT	QTY	RATE	AMOUNT
<b>2</b>	<b>LIGHT POINT WIRING</b>				
	SITC of following concealed point wiring using 1100V grade 3C x 1.5 sq.mm. copper conductor PVC insulated FRLS wires (with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to light points shall be drawn in flexible PVC conduit with adaptor & cover for junction box & crimp type lugs at both ends. Each circuit feeding not more than 10 points (200 watts). The rate shall include				
<b>a.</b>	<b>Primary Light points</b>	No	30.00		-
	Rate in words :-				
	SITC 5A Primary light points including MS concealed box, grid plate, 6A switch & circuit wiring.				
<b>b.</b>	<b>Secondary Light points</b>	No	5.00		-
	Rate in words :-				
	SITC 5A Secondary light points looped from primary light point. All MCB controlled light points will be considered as secondary light points.				
<b>c.</b>	<b>Primary light point on inverter</b>	No	12.00		0.00
	SITC 5A Primary light points including MS concealed box, grid plate, 6A switch & circuit wiring through Inverter DB				
<b>d.</b>	<b>Primary 5 A socket points</b>	No	4.00		-
	Rate in words :-				
	SITC <b>Primary 5 A Socket points</b> using circuit wiring (with proper color code) pulled through medium gauge PVC conduits.				
	Each point consisting of <b>1 Nos of 5 A sockets controlled by 1 Nos of 6A switch</b> , wired together forming a point with Green colour Earth wire.				
<b>e.</b>	<b>Secondary 5 A socket points (on Board plug points)</b>	No	12.00		-
	Rate in words :-				
	SITC <b>Secondary 5 A Socket points</b> using circuit wiring (with proper color code) pulled through heavy gauge PVC conduits. These points are installed on the Lighting Switch Board.				
	Each point consisting of <b>1 Nos of 5 A sockets controlled by 1 Nos of 6A switch</b> , wired together				

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
SR. NO.	ITEM	UNIT	QTY	RATE	AMOUNT
f.	<b>Exhaust fan/Wall Fan points</b>	No	3.00		-
	Rate in words :-				
	SITC of concealed point wiring for Exhaust fan and Wall fan using 1100V grade 3C x 1.5 sq.mm. copper conductor PVC insulated FRLS wires (with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to fan points shall be drawn in flexible PVC conduit with adaptor & cover for junction box & crimp type lugs at both ends. The rate shall include circuit wiring (2C x 2.5 sq.mm. + 1C x 1.0 sq.mm.) from Lighting DB to switchboard and to the Exhaust fan and Wall fan. (No seperate measurements for circuit wiring & PVC Conduits)				
	Each Exhaust Fan and wall fan will be operated on seperate switch, Rate should be including the cost of 5 A switch, 4 way closed 5A connector & Mounting Plates				
	<b>Wall Fan points on Inverter. The rate is inclusive of wires/ cables.</b>	No	7.00		0.00
	SITC of concealed point wiring for Wall fan using 1100V grade 3C x 1.5 sq.mm copper conductor PVC insulated FRLS wires				
	(with proper R,Y,B colour code) pulled through 25mm / 20mm Size, MMS Grade PVC conduits. All wiring below false ceiling shall be concealed. The wires from ceiling junction to fan points shall be drawn in flexible PVC conduit with adaptor & cover for iunction box &				
	The rate shall include circuit wiring (2C x 2.5 sq.mm. + 1C x 1.0 sq.mm.) from Lighting DB to switchboard and to the Exhaust fan and Wall fan. (No seperate measurements for circuit wiring & PVC Conduits)				
	Each wall fan will be operated on seperate switch, Rate should be including the cost of 5 A switch, 5 A socket, gang box & Mounting Plates				
g.	<b>Ceiling fan points</b>	No	5.00		-
	Rate in words :-				
	SITC Ceiling Fan point operated on seperate switch shall be Controlled by 2 Module, Step type Fan regulator, Rate should be including the cost of Fan hook, Suspending suitable fan rod, Connecting cord and Step type Fan Regulator				

SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH					
SR. NO.	ITEM	UNIT	QTY	RATE	AMOUNT
<b>h.</b>	<b>Bell points</b>	No	2.00		-
	Rate in words :-				
	SITC Bell point consisting of 5A Modular Bell switch & Suitable Bell, ( Bell switch to be installed in Manager Cabin and in Strong room. The Sound of both the bells should be different )				
	<b>C. TOTAL OF POINT WIRING</b>				-
<b>D</b>	<b>FIXTURES</b>				
	SITC of following concealed / surface mounted fixtures of makes as specified with all fixture accessories like suitable tubes/ bulbs/ ballast & internal wiring etc. The contractor has to assemble & install the said fixtures at position with necessary hardware required for installation like S-hook, chain link etc. as per requirement.				
<b>1</b>	<b>LED tube lights 4'</b>	No	15.00		-
	Rate in words :-				
	SITC 1200 mm Long Surface/Wall Mounted extruded Aluminium channels, with 20 w LED Tube light fixtures complete. Rate should be including the cost of Fixture, Suspending suitable rods, other accessories & hardware etc.				
	<b>Model</b> : BN021 LED25S 6500 PSU GR S1,				
	<b>Make</b> : Crompton <b>Model</b> : Linea LDLL20-CDL, LDLL20-WW				
	<b>Make</b> : Wipro, <b>Model</b> : Garnet D532065, D552065				
	<b>Make</b> : Havells <b>Model</b> : E-Lite LED Pride Pus LHEXBLP7PN1W020				
<b>2</b>	<b>LED tube lights 2'</b>	No	3.00		-
	Rate in words :-				
	SITC 600 mm Long Surface/Wall Mounted extruded Aluminium channels, with 10 w LED Tube light fixtures complete. Rate should be including the cost of Fixture, Suspending suitable rods, other accessories & hardware etc.				
<b>3</b>	<b>18 w Down lighter with LED</b>	No	15.00		-
	Rate in words :-				
	SITC 15 w White Powder Coated Housing LED Round / Square Down Lighter with High Efficiency LEDs & Ballasts				
	<b>Make</b> : Philips, <b>Model</b> : DN193B LED12S-6500 PSU WH S1				
	<b>Make</b> : Crompton, <b>Model</b> : Star Dura LDRSD-18W-CDL/ NW/ WW,				
	<b>Make</b> : Wipro, <b>Model</b> : Garnet Wave D541565, Infinity Wave DG11565, DG12065				
	<b>Make</b> : Havells, <b>Model</b> : Fazer Neo LHEBMCP7IW1W015, LHEBMCP7IW1W020				

<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>SR. NO.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
<b>4</b>	<b>600 x 600 mm square LED panel fittings</b>	No	14.00		-
	Rate in words :-				
	SITC 36 / 40 w LED Panel of 600mm X 600mm size, Square, Powder coated Recess mounting LED Light Fitting				
	Make: Philips, Model: RC380B G2 LED28S / RC140B G2 LED31S-6500 PSE OD WH				
	Make: Crompton, Model : LCTLR-36-CDL 36 w, LCPL-36-TL(2X2)				
	Make: Wipro, Model : Gartnet D424065, D414065 CRCO10R038HP57				
	Make : Havells, Model : Venus Neo PLR36WLED865PO, Plano PLR42WLED865S				
<b>5</b>	<b>Fans</b>				
	Supplying & Installing following mentioned Aluminum, medium duty, powder coated with glossy color Ceiling Fans / Wall Fans / Exhaust Fans with necessary clamps hook, bracket, hardware etc				
a.	SITC 1200 mm sweep Ceiling fans Complete with Mounting rod, Clamps, Locking pin etc. (Color -White / Ivory / Brown)	No	4.00		-
	Rate in words :-				
b.	SITC 250mm sweep Exhaust fan of metal body & blade with louvers on the outside	No	3.00		-
	Rate in words :-				
c.	SITC 400mm sweep Wall fan of 1350 RPM. Oscillating type, metal blades chrome plated guard with speed regulator and moisture proof treatment to winding and with 'E' class insulation.	No	7.00		-
	Rate in words :-				
	<b>D. TOTAL OF FIXTURES</b>				-
<b>E</b>	<b>EARTHING SYSTEM</b>				
<b>1</b>	<b>Plate Earthing</b>				
	S & I of Earthing Pit / Earth Electrode Station into the true ground level by using GI / Copper Plate type earthing with necessary excavation in soft soil, including Pouring Charcoal & Salt ( Approximately ) 50kg each per Pit with Predrilled 50mm dia B class GI Pipe-2.5 Mtr In length, GI Funnel with wiremesh, 35 x 5mm GI/Cu Earthing Strip, Complete job with necessary construction of appropriate sized Earthing PIT masonry Chamber with providing CI hinged chamber cover, Nutbolts, Earthing Testing Link, Hardware, Numbering of Chamber by using water proof paint. For more details refer IS 3043-1987 Brazing for Cu & Welding for GI Plate to pipe & Strip shall be done with coating by anti-corrosive paint				
a.	<b>GI Plate earthing.</b>	No	0.00		-

<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>SR. NO.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
	Rate in words :-				
	GI earthing pit made up of 600 x 600 x 6 mm thick, Hot dipped galvanized electrode including 25 x 5 mm the. GI strip.				
<b>b.</b>	<b>CU Plate earthing.</b>	No	4.00		-
	Rate in words :-				
	Copper earthing pit made up of 600 x 600 x 3 mm thick, copper electrode including 25 x 5 mm Copper strip.				
<b>2</b>	<b>Earthing Wires</b>				
	SITC of insulated copper earthing wire laid through 20 mm PVC conduits from separately made earth pit to the equipment in following sizes				
<b>a.</b>	<b>12 SWG cu bare wire for AC's &amp; DBs</b>	Rmt	0.00		-
	Rate in words :-				
<b>b.</b>	<b>25mm x 5 mm thick GI strip</b>	Rmt	10.00		-
	Rate in words :-				
<b>c.</b>	threaded, flexible copper wires/ cable laid through 20 mm size, MMS Grade PVC Conduites	Rmt	120.00		-
	Rate in words :-				
<b>3</b>	<b>Main Earth Bus</b>	No	2.00		-
	Supplying & Installing of Main bus for isolated earth comprising of 200mm x 40mm x 6mm thick copper bar fixed on insulated support and having 20 nos of holes and nut bolts studs for clamping the earth leads,all contained in MS/PVCbox of size 300mm x 200mm x 50mm deep and having transparent acrylic inspection cover as approved by Bank / Architect.				
	Rate in words :-				
	<b>E. TOTAL OF EARTHING SYSTEM</b>				-

<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>SR. NO.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
<b>F.</b>	<b>TELEPHONE / VOICE CABLING AND OUTLETS</b>				
<b>1</b>	<b>Telephone points</b>	No	1.00		-
	Rate in words :-				
	Providing and laying 2 Pair Grey Color 0.5mm Tinned Cu , PVC insulated cable for Telephone / Voice, laid through 20 / 25 mm size, MMS Grade PVC Conduites and Supplying & terminating with RJ-11 Telephone Jack / Outlet with face plates in suitable modular PVC / MS box from EPABX / Krone Tag Box to the work stations and terminate the other on a 10 pair Krone module installed in a Krone Tag box, complete with numbering of each cable with Ferule and Telephone Connection Chart <b>(No seperate measurements for PVC Conduits)</b>				
<b>2</b>	<b>Telephone cables</b>				
	Providing, laying and connecting PVC insulated copper telephone cable, laid through laid through 20 / 25 mm size, MMS Grade PVC conduites of following sizes including termination. <b>(No seperate measurements for PVC Conduits)</b>				
<b>a.</b>	<b>10-pair x 0.5 mm size Telephone cable, for MTNL / BSNL mains</b>	Rmt	0.00		-
	Rate in words :-				
<b>3</b>	<b>Telephone krone tag box</b>				
	Providing and fixing of <b>20 pair Krone Tag box</b> / 10 pair Krone type connector module housed in a Powder coated GI box with lockable cover of suitable size including termination complete with numbering of each cable with Ferule and a Telephone Connection chart.	No	0.00		-
	Rate in words :-				
	<b>F. TOTAL OF TELEPHONE SYSTEM</b>				-
<b>G</b>	<b>DATA CABLING SYSTEM</b>				
<b>1</b>	<b>Data points</b>	No	8.00		-
	Rate in words :-				
	Supplying and laying D-Link / Molex / Awaya / Amps make, Cat 6 cable for Data, laid through 20/25 mm size, MMS Grade PVC conduites and providing & terminating with RJ-45 Information Outlet Ports with face plates in suitable modular PVC / MS box from Server Rack/ Patch Panel/ Data Switch to individual work stations & terminating other end with RJ-45 connector including numbering with ferule <b>(No seperate measurements for PVC Conduits)</b>				
<b>2</b>	<b>Supplying &amp; laying Cat-6, RJ-45, 1 m. length Data Patch Cords,</b>	No	9.00		-
	<b>Make</b> : D-Link / Molex / Awaya				
	Rate in words :-				

<b>SOQ FOR ELECTRICAL WORKS IN NATEPUTE BRANCH</b>					
<b>Sr. No.</b>	<b>ITEM</b>	<b>UNIT</b>	<b>QTY</b>	<b>RATE</b>	<b>AMOUNT</b>
<b>3</b>	<b>Supplying &amp; laying Cat-6, RJ-45, 2 met length Data Patch Cords,</b> Make : D-Link / Molex / Aways Rate in words :-	No	8.00		-
<b>4</b>	<b>Patch panel</b>				
<b>a.</b>	Supplying and Installing D-Link make, preloaded, Cat 6, RJ-45, 24 Port Patch Panel, complete with terminations & numbering with ferule Rate in words :-	No	1.00		-
<b>5</b>	Supplying & Installing D-Link / HCL / iBall make 9-U <b>Networking Wall mounting rack</b> , complete with following mentioned accessories * 2U Horizontal Cable Manager * Power Distribution Unit / Power Strip of 6 Sockets * Cooling Fans * Cantilever Trays / Shelves * Hardware Packet Rate in words :-	No	1.00		-
<b>G. TOTAL OF DATA CABLING SYSTEM</b>					<b>-</b>
<b>H</b>	<b>MISCELLANEOUS WORKS</b>				
	<b>Temporery Lightning supply &amp; data connectivity</b>				
<b>1</b>	Arranging temporary Power, data supply & Lighting for all agencies and for staff PCs at work place . The rate shall include statutory aproval from Local MSEDCL / Electrical Inspectorate & other required satatutory bodies, preparation of AS-BUILT drawings, Testing of the installation & preparaiton of test report as required by statutory bodies. Note: The rate to include cost of suitable temporary Lighting for all areas as per requirement during work.	<b>Job</b>	1.00		-
<b>H. TOTAL FOR MISCELLANEOUS</b>					<b>-</b>
<b>TOTAL FOR ELECTRICAL WORKS</b>					<b>-</b>